



1 **EU-TYPE EXAMINATION CERTIFICATE**

2 Equipment intended for use in Potentially Explosive Atmospheres Directive 2014/34/EU

3 Certificate Number: **Sira 04ATEX2302X** Issue: **8**

4 Equipment: **IS-L101L Beacon and IS-DL105 Sounder/Beacon**

5 Applicant: **European Safety System Limited**

6 Address: Impress House  
Mansell Road  
Acton  
London W3 7QH  
UK

7 This equipment and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.

8 CSA Group Netherlands B.V., Notified Body Number 2813 in accordance with Articles 17 and 21 of Directive 2014/34/EU of the European Parliament and of the Council, dated 26 February 2014, certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in the confidential reports listed in Section 14.2.

9 Compliance with the Essential Health and Safety Requirements, with the exception of those listed in the schedule to this certificate, has been assured by compliance with the following documents:

EN IEC 60079-0:2018

EN 60079-11:2012

10 If the sign 'X' is placed after the certificate number, it indicates that the equipment is subject to Specific Conditions of Use identified in the schedule to this certificate.

11 This EU-Type Examination Certificate relates only to the design and construction of the specified equipment. If applicable, further requirements of this Directive apply to the manufacture and supply of this equipment.

12 The marking of the equipment shall include the following:



II 1 G  
Ex ia IIC T4 Ga (-40°C ≤ Ta ≤ +60°C)

Project Number 1698

Signed: 

Title: Director of Operations

This certificate and its schedules may only be reproduced in its entirety and without change

**CSA Group Netherlands B.V.**  
Utrechtseweg 310,  
6812 AR, Arnhem,  
Netherlands



## SCHEDULE

### EU-TYPE EXAMINATION CERTIFICATE

Sira 04ATEX2302X  
Issue 8

#### 13 DESCRIPTION OF EQUIPMENT

The IS-L101L Beacon is designed to provide a flashing warning when activated. It consists of two printed circuit board assemblies, one containing the main circuit and the other several LEDs. These are mounted inside an IP 66, flame retardant, ABS enclosure that is fitted with a transparent polycarbonate 'lens'. Two, alternative LED boards may be fitted, each being fitted with different types of LED.

External connections are made to terminals mounted on the main printed circuit board via cable entry devices mounted in the walls of the enclosure.

**Terminal + w.r.t. Terminal:**

$U_i = 28 \text{ V}$
$I_i = 660 \text{ mA}$
$P_i = 1.2 \text{ W}$
$C_i = 0$
$L_i = 0$

**Terminal S+ w.r.t. Terminal S:**

$U_o = 16.8 \text{ V}$
$I_o = 660 \text{ mA}$
$P_o = 1.2 \text{ W}$

The parameters above are based on Terminal + being considered internally electrically connected to Terminal S+ via internal voltage clamping zener diodes of maximum voltage 16.8V and Terminal - being considered internally electrically connected to Terminal S -.

**Terminals Ac.Sw:**

$U_o = 16.8 \text{ V}$
$I_o = 3.61 \text{ mA}$
$P_o = 15.2 \text{ mW}$

**Variation 1** - This variation introduced the following changes:

- Following appropriate re-assessment to demonstrate compliance with the requirements of the latest standards, the documents originally listed in section 9, EN 50014: 1997 + A1 and A2, EN 50020: 2002 and EN 50284: 1999, were replaced by those currently listed, the markings in section 12 were updated accordingly.
- The IS-L101L Beacon was changed to modify the PCB track and component layout.

**Variation 2** - This variation introduced the following change:

- The use of a cast aluminium enclosure material as an alternative to the existing plastic material was approved. The Special conditions for Safe Use were amended to reflect this change.



**SCHEDULE**

**EU-TYPE EXAMINATION CERTIFICATE**

**Sira 04ATEX2302X  
Issue 8**

**Variation 3** - This variation introduced the following change:

- i. It was clarified that the cast aluminium enclosure versions that were first recognised in Issue 4 of this certificate are in fact the model IS-DL105 Combined Sounder/Beacon; to account for the new model, the Special Conditions for Safe Use and associated drawings were reviewed and revised accordingly. The IS-DL105 is described below:

The IS-DL105 Sounder/Beacon is designed to provide an audible and flashing warning when activated. It consists of three printed circuit board assemblies, one for the sounder, connected to an inductive sounder transducer; and two printed circuit board assemblies for the beacon, one containing the main circuit and the other several LEDs.

These are mounted in an IP 66, cast aluminium enclosure with a borosilicate glass dome. External connections are made to terminals mounted on the printed circuit board via a cable entry device mounted in the wall of the enclosure.

Two alternative LED boards may be fitted, each being fitted with different types of LED. External connections are made to terminals mounted on the main printed circuit board via cable entry devices mounted in the walls of the enclosure.

Sounder and Beacon powered through a single barrier		
The barrier may be connected either to the Sounder or to the Beacon, as shown below:		
Sounder PCBA	<b>OR</b>	Beacon PCBA
Input to Terminals + w.r.t. Terminal:		Input to Terminals + w.r.t. Terminals -:
$U_i = 28\text{ V}$ $I_i = 93\text{ mA}$ $P_i = 660\text{ mW}$ $C_i = 0$ $L_i = 0$		$U_i = 28\text{ V}$ $I_i = 93\text{ mA}$ $P_i = 660\text{ mW}$ $C_i = 0$ $L_i = 0$
In addition, a diode return barrier or isolator may be connected to Terminal S2 w.r.t. Terminal – and Terminal S3 w.r.t. Terminal – with the following parameters: $U_i = 28\text{ V}$ $I_i = 0$		The output parameters at Terminal S+ w.r.t. Terminal S- are: $U_o = 16.8\text{ V}$ $I_o = 93\text{ mA}$ $P_o = 660\text{ mW}$ These are based on Terminal + being considered internally electrically connected to Terminal S+ via internal voltage clamping zener diodes of maximum voltage 16.8V and Terminal - being considered internally electrically connected to Terminal S -.
		The output parameters at Terminals Ac.Sw are: $U_o = 16.8\text{ V}$ $I_o = 3.61\text{ mA}$ $P_o = 15.2\text{ mW}$



## SCHEDULE

### EU-TYPE EXAMINATION CERTIFICATE

Sira 04ATEX2302X  
Issue 8

Sounder and Beacon powered through two separate barriers		
One barrier may be connected to the Sounder and a second to the Beacon, as shown below. The Sounder and Beacon shall be regarded as separate intrinsically safe circuits and shall not be electrically connected to each other.		
Sounder PCBA	<b>AND</b>	Beacon PCBA
Input to Terminals + w.r.t. Terminal -:		Input to Terminals + w.r.t. Terminals -:
$U_i = 28\text{ V}$ $I_i = 93\text{ mA}$ $P_i = 660\text{ mW}$ $C_i = 0$ $L_i = 0$		$U_i = 28\text{ V}$ $I_i = 660\text{ mA}$ $P_i = 1.2\text{ W}$ $C_i = 0$ $L_i = 0$
In addition, a diode return barrier or isolator may be connected to Terminal S2 w.r.t. Terminal - and Terminal S3 w.r.t. Terminal - with the following parameters: $U_i = 28\text{ V}$ $I_i = 0$		The output parameters at Terminal S+ w.r.t. Terminal S- are: $U_o = 16.8\text{ V}$ $I_o = 660\text{ mA}$ $P_o = 1.2\text{ W}$ These are based on Terminal + being considered internally electrically connected to Terminal S+ via internal voltage clamping zener diodes of maximum voltage 16.8V and Terminal - being considered internally electrically connected to Terminal S-.
		The output parameters at Terminals Ac.Sw are: $U_o = 16.8\text{ V}$ $I_o = 3.61\text{ mA}$ $P_o = 15.2\text{ mW}$

**Variation 4** - This variation introduced the following changes:

- i. Following appropriate assessment to demonstrate compliance with the latest technical knowledge, the documents previously listed, EN 60079-0:2006, EN 60079-11:2007 and EN 60079-26:2007 were replaced by EN 60079-0:2012, EN 60079-11:2012 and IEC 60079-26:2014 Ed 3.0.

**Variation 5** - This variation introduced the following changes:

- i. Following appropriate assessment to demonstrate compliance with the latest technical knowledge, the document previously listed, EN 60079-0:2012 was replaced by EN IEC 60079-0:2018.
- ii. IEC 60079-26:2014 Ed 3.0 was removed as IEC 60079-26 is not applicable to Ex ia Ga equipment.

## 14 DESCRIPTIVE DOCUMENTS

### 14.1 Drawings

Refer to Certificate Annexe.

### 14.2 Associated Sira Reports and Certificate History

Issue	Date	Report no.	Comment
0	24 November 2004	R52A12120A	The release of the prime certificate.
1	14 October 2005	R52A14095A	Issued to introduce the changes described in report number R52A14095A.

This certificate and its schedules may only be reproduced in its entirety and without change

CSA Group Netherlands B.V.  
Utrechtseweg 310,  
6812 AR, Arnhem Netherlands



## SCHEDULE

### EU-TYPE EXAMINATION CERTIFICATE

**Sira 04ATEX2302X**  
**Issue 8**

2	18 August 2006	R52A15304A	Issued to introduce the changes described in report number R52A15304A
3	23 November 2009	R20910A	This Issue covers the following changes: <ul style="list-style-type: none"><li>All previously issued certification was rationalised into a single certificate, Issue 3, Issues 0 to 2 referenced above are only intended to reflect the history of the previous certification and have not been issued as documents in this format.</li><li>The introduction of Variation 1.</li></ul>
4	08 August 2013	R28860A/00	The introduction of Variation 2.
5	31 October 2013	R31828A/00	The introduction of Variation 3.
6	23 February 2015	R70006449B	The introduction of Variation 4.
7	05 September 2019	R80009717A	This Issue covers the following changes: <ul style="list-style-type: none"><li>EC Type-Examination Certificate in accordance with 94/9/EC updated to EU Type-Examination Certificate in accordance with Directive 2014/34/EU. <i>(In accordance with Article 41 of Directive 2014/34/EU, EC Type-Examination Certificates referring to 94/9/EC that were in existence prior to the date of application of 2014/34/EU (20 April 2016) may be referenced as if they were issued in accordance with Directive 2014/34/EU. Variations to such EC Type-Examination Certificates may continue to bear the original certificate number issued prior to 20 April 2016.)</i></li></ul> The introduction of Variation 5.
8	15th October 2019	1698	<ul style="list-style-type: none"><li>Transfer of certificate <b>Sira 04ATEX2302X</b> from Sira Certification Service to CSA Group Netherlands B.V..</li></ul>

#### 15 SPECIAL CONDITIONS FOR SAFE USE (denoted by X after the certificate number)

- 15.1 The enclosure of the IS-L101L Beacon is non-conducting and may generate an ignition-capable level of electrostatic charges under certain extreme conditions. The user should ensure that the equipment is not installed in a location where it may be subjected to external conditions that might cause a build-up of electrostatic charges on non-conducting surfaces, additionally, cleaning of the equipment should be done only with a damp cloth.
- 15.2 The equipment has an ingress protection rating of IP 66. However, if it has been supplied without cable entry devices, then the user shall ensure that the devices that are fitted will provide an ingress protection that is appropriate to the environment in which it is installed i.e. IP20 or better. If only one of the two cable entries are used, then the unused entry shall be fitted with a blanking device that ensures ingress protection appropriate to the environment in which it is installed i.e. IP20 or better.
- 15.3 The enclosure of the IS-DL105 Sounder/Beacon is manufactured from cast aluminium. In rare cases, ignition sources due to impact and friction sparks could occur. This shall be considered during installation, particularly if the equipment is installed in an area requiring Equipment Protection Level Ga.
- 15.4 When the IS-DL105 Sounder/Beacon is powered via two separate barriers, they shall be installed as separate intrinsically safe circuits; the Sounder shall not be electrically connected to the Beacon and they shall not share a common return line.

This certificate and its schedules may only be reproduced in its entirety and without change

**CSA Group Netherlands B.V.**  
Utrechtseweg 310,  
6812 AR, Arnhem Netherlands



## **SCHEDULE**

### **EU-TYPE EXAMINATION CERTIFICATE**

**Sira 04ATEX2302X  
Issue 8**

16 **ESSENTIAL HEALTH AND SAFETY REQUIREMENTS OF ANNEX II (EHSRs)**

The relevant EHSRs that are not addressed by the standards listed in this certificate have been identified and individually assessed in the reports listed in Section 14.2.

# Certificate Annexe



**Certificate Number:** Sira 04ATEX2302X

**Equipment:** IS-L101L Beacon and IS-DL105 Sounder/Beacon

**Applicant:** European Safety System Limited

**Issue 0 to 2** (The drawings listed with these Issues were rationalised and superseded by those detailed in Issue 2)

## Issue 2

Drawing No.	Sheets	Rev.	Date	Title
CD 4621	1 of 1	A	03 Dec 04	Circuit Diagram
PL 4621	1 of 1	A	03 Dec 04	Parts List
D 4621	1 of 1	A	03 Dec 04	General Arrangement
D 4622	1 of 1	C	02 May 06	Certification Label - ATEX
D 4623	1 of 1	A	07 Dec 04	Printed Circuit Board
D 4628	1 of 1	C	17 Feb 06	Certification Label ATEX/IECEX/FM

## Issue 3

Drawing No.	Sheets	Rev.	Date (Sira stamp)	Title
D 4628	1 of 1	D	11 Nov 09	IS-L101L Beacon Label (ATEX, IECEX, FM)
D 4623	1 of 1	B	11 Nov 09	Printed Circuit Board

## Issue 4

Drawing no.	Sheets	Rev.	Date (Sira stamp)	Title
D187-00-201-SC	1 of 1	A	08 May 13	IS-DL105 Sounder Beacon GA

Drawing D187-00-001-SC was previously listed in error and was removed.

## Issue 5

Drawing no.	Sheets	Rev.	Date	Title
CD4521	1 of 1	A	02 Nov 04	IS-A105N Sounder – circuit diagram
D187-99-201-SC	1 of 1	B	24 Oct 13*	IS-DL105 Sounder/Beacon - label
D4524	1 of 1	A	25 Oct 04	IS-A105N Sounder - artwork
D4525	1 of 1	A	01 Nov 04	IS-A105N Sounder – assembly
PL4521	1 of 1	A	02 Nov 04	IS-A105N Sounder – parts list

\* This is the date that the drawing was stamped by Sira.

**Issue 6** No new drawings were introduced.

**Issue 7** - No new drawings were introduced.

This certificate and its schedules may only be reproduced in its entirety and without change

**CSA Group Netherlands B.V.**  
Utrechtseweg 310,  
6812 AR, Arnhem,  
Netherlands